


MAGLATCH™
ADDITIONAL FEATURES & CUSTOM MODELS

Removable Spindle



UG Trim Only

Replacing a vandalized mortise lock can be accomplished quickly and easily without removing the trim from the door. The round cap on the interior lever may be removed via a special allen key. The spindle can then be pulled out, which allows the lockset to be replaced.

Quick-Switch Cylinder Protector



UG Trim Only

Changing a cylinder also does not require removing the trim from the door. An access hole in the interior trim allows an allen key to be inserted into the cylinder locking post of the exterior trim. The locking post can be turned, which releases the cylinder and allows the switch.



MagChannel

For use on inswing doors, MagChannel allows installation of the electromagnetic lock without unsightly "Z" brackets.

Custom Electromagnetic Locks




MAGLATCH can work with existing or new electromagnetic locks. MAGLATCH models which include an electromagnetic lock are furnished with a slim design 1,200 lb. holding force magnet and armature. Custom electromagnetic locks can be furnished with options such as "Bond Sensors" and "Door Status Sensors" to meet access control system needs. Contact factory for details.

Load Bearing Switches



Both the interior and exterior levers contain independent switches, rated at 5Amps, 30vDC. These can interrupt the electromagnetic lock's power and have a mechanical life of 10 million cycles. Depressing the lever opens the circuit.

Exit Devices



A full range of exit devices, including rim, mortise, surface vertical rod and concealed vertical rod models are available. See High-Security Exit Device Section for catalog cut.

Power Supplies



Securitech offers a full range of power supplies for the MAGLATCH system. Custom requests can be accommodated. See the full catalog cut.

Special Elements

KU Key Usage Signal Switch

For use with access control systems. Sends a signal to the access control system that a key was used for entry as opposed to the access control card.

LL 8' Lead Length For Easy Wiring

Eliminates wiring connections in the lock area of the door.

Special Models: Functions & Operating Modes

| Designation | Name | Normal Operation | Loss of Power | | Note |
|-------------|------------------|--|---------------|-------------|---|
| | | | Exit | Entry | |
| 9041 | DoubleLock 1 | Locked Exit & Entry | Fail-Safe | Fail-Secure | Includes electromagnetic lock with bond sensor |
| 9042 | DoubleLock 2 | Locked Exit & Entry | Fail-Secure | Fail-Secure | Includes electromagnetic lock with bond sensor |
| 9027 | Exit Only-Locked | Key or Card Required For Exit (No Entry) | Fail-Secure | None | Check code requirements! Electromagnetic lock by others |
| 9051 | Timed UnLock 1 | Free Exit, Exterior Unlocked By Timer For Defined Time | Fail-Safe | Fail-Safe | Requires custom Securitech power supply Include electromagnetic lock |
| 9052 | Timed UnLock 2 | Free Exit, Exterior Unlocked By Timer For Defined Time | Fail-Safe | Fail-Secure | Requires custom Securitech power supply Include electromagnetic lock |

Additional functions can be created to meet specific needs. Please check local codes and requirements prior to specification and installation. Securitech assumes no responsibility or liability for code compliance.

l:\mark3\lit & stuff\l\ binder 200111 newA25 CAT Maglatch Custom Models V3.vsd\page-1.las 03/25/02

made in u.s.a.